

COACH MODEL : Model Year 2014 – 2019 CX 45 with DMUX

DATE : December 07, 2022

SUBJECT : Fog light Control and wiring schematic explanation

Troubleshooting the fog lights using the VanHool schematic can be a little confusing due to translation and a mislabeled relay.

Page 36A (exterior lighting) nomenclature identifies L038.1 and L038.2 as the left and right foglamps. RL027 is shown as the foglamp relay. Both the lights and the relay are not shown in the schematic of page 36A.

The fog lights are shown on the cornering light page (300). RL032 sends voltage from Z21 to the middle plug, pin 2 of the cornering module which sends power out of the 4 pin plug, pins 3 and 4 to the left and right foglamps. The module supplies +24 volts to the foglamps and supplies the ground.

